

PZ-770 AMPLIFIER

Description:- This model is a modestly powered PA mixer amplifier, suitable for environments like small event spaces, classrooms, or retail settings. Its multiple mic inputs, tone control flexibility, built-in MP3 playback, and support for both low-impedance and line-level.

Key Specification:-

- Speaker/Driver selector disables bass boost when using driver units for safe operation.
- Works on AC mains and 12V DC battery—useful for outdoor or backup use.
- 4 Mic & 1 aux inputs with built-in digital player & bluetooth connectivity.
- Instant transfer to DC power if AC power fails.

Features:-

MODEL NO.	PZ-770
POWER OUTPUT	100 W MAX
TONE CONTROL	BASS, TREBLE
INPUT CHANNELS	4 x Mic 0.8mV
FREQUENCY RESPONSE	50-15,000 Hz
SIGNAL TO NOISE RATIO	60dB
POWER SUPPLY	220~240v, 50/60Hz
SPEAKER OUTPUT	4Ω, 8Ω, 16Ω, 100V
WEIGHT	8.80 KG



PZ-770