

## SSA-300DX AMPLIFIER

**Description:-** The Penza SSA-300DX is a robust and flexible PA amplifier tailored for diverse environments schools, religious venues, factories, or events. Its multiple mic/aux inputs, built in media playback, tone control, and fail-safe power backup.

### Key Specification:-

- Pre-amplifier and line output for connecting to a booster amplifier and for recording the program.
- Line input for connecting the output from any external mixer or permitting SSA-350DP USB to be used as a booster power amplifier.
- 6 Mic & 2 aux inputs with built-in digital player & bluetooth connectivity.
- Instant transfer to DC power if AC power fails.

### Features:-

MODEL NO.	SSA-300DX
POWER OUTPUT	450 W MAX
TONE CONTROL	BASS, TREBLE
INPUT CHANNELS	6 x Mic 0.8mV
FREQUENCY RESPONSE	50-15,000 Hz
SIGNAL TO NOISE RATIO	60dB
POWER SUPPLY	220~240v, 50/60Hz
SPEAKER OUTPUT	4Ω, 8Ω, 70/100V
WEIGHT	14.50 KG



**SSA-300DX**